



<https://cnhisolar.net/>



A large, stylized graphic element is positioned diagonally across the page. It features a yellow trapezoid on the left, a smaller tan trapezoid nested within it, and a long, thin grey parallelogram extending from the right side of the tan trapezoid towards the top right corner of the page.

BUSINESS BROCHURE

1993-NOW

FOCUS OVER 30 YEARS
ALWAYS INNOVATE AND LEAD

<https://cnhisolar.net/>

ZHEJIANG JINGYING NEW ENERGY CO.,LTD

Add: Room 102-1, Building 8, Robot Industrial Park, No. 176, Yanyun Road,

Kunpeng Street, Dongtou District, Wenzhou, Zhejiang

TEL: +8613905874507

<https://cnhisolar.net/> hisolar@cnhisolar.com

We sincerely hope that the manual could bring you convenience!
We reserve the rights of modification for the standard, technical specification and size which referred in this manual, because
of service improvement and market going. Forgive no further notice if any modification.
All copyrights of written informations and pictures belong to our company. Reprinting and piracy are prohibited.



PURE SINE WAVE POWER INVERTER

Over voltage protection



Low voltage protection



Over load protection



Over temperature protection




150W Pure sine wave power inverter



Technical parameters

Model	P-150W-12V	P-150W-24V	P-150W-48V
Rated Power	150W		
Peak Power	300W		
DC Input Voltage Range	DC12V(9.5V-15.5V)	DC24V(19V-31V)	DC48V(38V-62V)
AC Output Voltage (Single Choice)	100V/110V/120V/220V/230V/240V		
Unload Current	≤0.55A	≤0.3A	≤0.18A
Output Frequency	(50Hz±2Hz) or (60Hz±2Hz)		
Output Waveform	Pure sine wave		
Display	/		
USB Output Voltage / Current	5V@3.4A,9V@2A,12V@1.5A (Support QC3.0 fast charge up to 18W)		
Max. Output Efficiency	89%	91%	93%
Low Voltage Protection	"Alarm ""Bi"" with 2s interval +red and green lights flashing alternately restart automatically when voltage recover"		
Over Voltage Protection	" Alarm ""BiBi"" with 1s interval +red and green lights flashing alternately restart automatically when voltage recover"		
Over Load Protection	"Alarm ""Bi"" continuously +red light flashing / restart automatically when load power recover; If it is closed after twice recover, it need restart manually."		
Over Temp Protection	" Alarm ""BiBiBi"" with 1s interval +red and green lights flashing alternately restart when temp recover"		
Short Circuit Protection	Yes		
DC Reverse Connection Protection	Fuse burnt		
Low Voltage Alarm Range	10.5v±0.5v	21v±0.5v	42v±0.5v
Low Voltage Protection Range	9.5v±0.5v	19v±0.5v	38v±0.5v
Low Voltage Recover Range	12v±0.5v	23v±0.5v	46v±0.5v
Over Voltage Protection Range	15.5v±0.5v	31v±0.5v	62v±0.5v
Over Voltage Recover Range	14v±0.5v	28v±0.5v	56v±0.5v
Working Temperature	-10°C~50°C		
Cooling Method	Fan cooling (Temperature control)		
Unit Size (mm)			
N.W/G.W(kg)			


300W Pure sine wave power inverter



Technical parameters

Model	P-300W-12V	P-300W-24V	P-300W-48V
Rated Power	300W		
Peak Power	600W		
DC Input Voltage Range	DC12V(9.5V-15.5V)	DC24V(19V-31V)	DC48V(38V-62V)
AC Output Voltage (Single Choice)	100V/110V/120V/220V/230V/240V		
Unload Current	≤0.55A	≤0.3A	≤0.18A
Output Frequency	(50Hz±2Hz) or (60Hz±2Hz)		
Output Waveform	Pure sine wave		
Display	/		
USB Output Voltage / Current	5V@3.4A,9V@2A,12V@1.5A (Support QC3.0 fast charge up to 18W)		
Max. Output Efficiency	89%	91%	93%
Low Voltage Protection	"Alarm ""Bi"" with 2s interval +red and green lights flashing alternately restart automatically when voltage recover"		
Over Voltage Protection	" Alarm ""BiBi"" with 1s interval +red and green lights flashing alternately restart automatically when voltage recover"		
Over Load Protection	"Alarm ""Bi"" continuously +red light flashing / restart automatically when load power recover; If it is closed after twice recover, it need restart manually."		
Over Temp Protection	" Alarm ""BiBiBi"" with 1s interval +red and green lights flashing alternately restart when temp recover"		
Short Circuit Protection	Yes		
DC Reverse Connection Protection	Fuse burnt		
Low Voltage Alarm Range	10.5v±0.5v	21v±0.5v	42v±0.5v
Low Voltage Protection Range	9.5v±0.5v	19v±0.5v	38v±0.5v
Low Voltage Recover Range	12v±0.5v	23v±0.5v	46v±0.5v
Over Voltage Protection Range	15.5v±0.5v	31v±0.5v	62v±0.5v
Over Voltage Recover Range	14v±0.5v	28v±0.5v	56v±0.5v
Working Temperature	-10°C~50°C		
Cooling Method	Fan cooling (Temperature control)		
Unit Size	199mm*106mm*60mm		
N.W/G.W	0.8kg/1.06kg		


500W Pure sine wave power inverter



Technical parameters

Model	P-500W-12V	P-500W-24V	P-500W-48V
Rated Power	500W		
Peak Power	1000W		
DC Input Voltage Range	DC12V(9.5V-15.5V)	DC24V(19V-31V)	DC48V(38V-62V)
AC Output Voltage (Single Choice)	100V/110V/120V/220V/230V/240V		
Unload Current	≤0.6A	≤0.3A	≤0.2A
Output Frequency	(50Hz±2Hz) or (60Hz±2Hz)		
Output Waveform	Pure sine wave		
Display	/		
USB Output Voltage / Current	5V@3.4A,9V@2A,12V@1.5A (Support QC3.0 fast charge up to 18W)		
Max. Output Efficiency	88%	90%	92%
Low Voltage Protection	"Alarm ""Bi"" with 2s interval +red and green lights flashing alternately restart automatically when voltage recover"		
Over Voltage Protection	" Alarm ""BiBi"" with 1s interval +red and green lights flashing alternately restart automatically when voltage recover"		
Over Load Protection	"Alarm ""Bi"" continuously +red light flashing / restart automatically when load power recover; If it is closed after twice recover, it need restart manually."		
Over Temp Protection	" Alarm ""BiBiBi"" with 1s interval +red and green lights flashing alternately restart when temp recover"		
Short Circuit Protection	Yes		
DC Reverse Connection Protection	Fuse burnt		
Low Voltage Alarm Range	10.5v±0.5v	21v±0.5v	42v±0.5v
Low Voltage Protection Range	9.5v±0.5v	19v±0.5v	38v±0.5v
Low Voltage Recover Range	12v±0.5v	23v±0.5v	46v±0.5v
Over Voltage Protection Range	15.5v±0.5v	31v±0.5v	62v±0.5v
Over Voltage Recover Range	14v±0.5v	28v±0.5v	56v±0.5v
Working Temperature	-10°C~50°C		
Cooling Method	Fan cooling (Temperature control)		
Unit Size	245mm*106mm*60mm		
N.W/G.W	1.06kg/1.34kg		


600W Pure sine wave power inverter



Technical parameters

Model	P-600W-12V	P-600W-24V	P-600W-48V
Rated Power	600W		
Peak Power	1200W		
DC Input Voltage Range	DC12V(9.5V-15.5V)	DC24V(19V-31V)	DC48V(38V-62V)
AC Output Voltage (Single Choice)	100V/110V/120V/220V/230V/240V		
Unload Current	≤0.6A	≤0.3A	≤0.2A
Output Frequency	(50Hz±2Hz) or (60Hz±2Hz)		
Output Waveform	Pure sine wave		
Display	/		
USB Output Voltage / Current	5V@3.4A,9V@2A,12V@1.5A (Support QC3.0 fast charge up to 18W)		
Max. Output Efficiency	88%	90%	92%
Low Voltage Protection	"Alarm ""Bi"" with 2s interval +red and green lights flashing alternately restart automatically when voltage recover"		
Over Voltage Protection	" Alarm ""BiBi"" with 1s interval +red and green lights flashing alternately restart automatically when voltage recover"		
Over Load Protection	"Alarm ""Bi"" continuously +red light flashing / restart automatically when load power recover; If it is closed after twice recover, it need restart manually."		
Over Temp Protection	" Alarm ""BiBiBi"" with 1s interval +red and green lights flashing alternately restart when temp recover"		
Short Circuit Protection	Yes		
DC Reverse Connection Protection	Fuse burnt		
Low Voltage Alarm Range	10.5v±0.5v	21v±0.5v	42v±0.5v
Low Voltage Protection Range	9.5v±0.5v	19v±0.5v	38v±0.5v
Low Voltage Recover Range	12v±0.5v	23v±0.5v	46v±0.5v
Over Voltage Protection Range	15.5v±0.5v	31v±0.5v	62v±0.5v
Over Voltage Recover Range	14v±0.5v	28v±0.5v	56v±0.5v
Working Temperature	-10°C~50°C		
Cooling Method	Fan cooling (Temperature control)		
Unit Size	245mm*106mm*60mm		
N.W/G.W	1.06kg/1.34kg		



1000W Pure sine wave power inverter



Technical parameters

Model	P-1000W-12V	P-1000W-24V	P-1000W-48V
Rated Power	1000W		
Peak Power	2000W		
DC Input Voltage Range	DC12V(9.5V-15.5V)	DC24V(19V-31V)	DC48V(38V-62V)
AC Output Voltage (Single Choice)	100V/110V/120V/220V/230V/240V		
Unload Current	≤0.6A	≤0.3A	≤0.2A
Output Frequency	(50Hz±2Hz) or (60Hz±2Hz)		
Output Waveform	Pure sine wave		
Display	/		
USB Output Voltage / Current	5V@3.4A,9V@2A,12V@1.5A (Support QC3.0 fast charge up to 18W)		
Max. Output Efficiency	88%	90%	92%
Low Voltage Protection	"Alarm ""Bi"" with 2s interval +red and green lights flashing alternately restart automatically when voltage recover"		
Over Voltage Protection	" Alarm ""BiBi"" with 1s interval +red and green lights flashing alternately restart automatically when voltage recover"		
Over Load Protection	"Alarm ""Bi"" continuously +red light flashing / restart automatically when load power recover; If it is closed after twice recover, it need restart manually."		
Over Temp Protection	" Alarm ""BiBiBi"" with 1s interval +red and green lights flashing alternately restart when temp recover"		
Short Circuit Protection	Yes		
DC Reverse Connection Protection	Fuse burnt		
Low Voltage Alarm Range	10.5v±0.5v	21v±0.5v	42v±0.5v
Low Voltage Protection Range	9.5v±0.5v	19v±0.5v	38v±0.5v
Low Voltage Recover Range	12v±0.5v	23v±0.5v	46v±0.5v
Over Voltage Protection Range	15.5v±0.5v	31v±0.5v	62v±0.5v
Over Voltage Recover Range	14v±0.5v	28v±0.5v	56v±0.5v
Working Temperature	-10°C~50°C		
Cooling Method	Fan cooling (Temperature control)		
Unit Size	295mm*135mm*76mm		
N.W/G.W	1.9kg/2.35kg		

1200W Pure sine wave power inverter



Technical parameters

Model	P-1200W-12V	P-1200W-24V	P-1200W-48V
Rated Power	1200W		
Peak Power	2400W		
DC Input Voltage Range	DC12V(9.5V-15.5V)	DC24V(19V-31V)	DC48V(38V-62V)
AC Output Voltage (Single Choice)	100V/110V/120V/220V/230V/240V		
Unload Current	≤0.6A	≤0.3A	≤0.2A
Output Frequency	(50Hz±2Hz) or (60Hz±2Hz)		
Output Waveform	Pure sine wave		
Display	LED or LCD display		
USB Output Voltage / Current	5V@3.4A,9V@2A,12V@1.5AA (Support QC3.0 fast charge up to 18W)		
Max. Output Efficiency	88%	90%	92%
Low Voltage Protection	"Alarm ""Bi"" with 2s interval +red and green lights flashing alternately restart automatically when voltage recover"		
Over Voltage Protection	" Alarm ""BiBi"" with 1s interval +red and green lights flashing alternately restart automatically when voltage recover"		
Over Load Protection	"Alarm ""Bi"" continuously +red light flashing / restart automatically when load power recover; If it is closed after twice recover, it need restart manually."		
Over Temp Protection	" Alarm ""BiBiBi"" with 1s interval +red and green lights flashing alternately restart when temp recover"		
Short Circuit Protection	Yes		
DC Reverse Connection Protection	Fuse burnt		
Low Voltage Alarm Range	10.5v±0.5v	21v±0.5v	42v±0.5v
Low Voltage Protection Range	9.5v±0.5v	19v±0.5v	38v±0.5v
Low Voltage Recover Range	12v±0.5v	23v±0.5v	46v±0.5v
Over Voltage Protection Range	15.5v±0.5v	31v±0.5v	62v±0.5v
Over Voltage Recover Range	14v±0.5v	28v±0.5v	56v±0.5v
Working Temperature	-10°C~50°C		
Cooling Method	Fan cooling (Temperature control)		
Unit Size	295mm*135mm*76mm		
N.W/G.W	1.9kg/2.35kg		

1500W Pure sine wave power inverter



Technical parameters

Model	P-1500W-12V	P-1500W-24V	P-1500W-48V
Rated Power	1500W		
Peak Power	3000W		
DC Input Voltage Range	DC12V(9.5V-15.5V)	DC24V(19V-31V)	DC48V(38V-62V)
AC Output Voltage (Single Choice)	100V/110V/120V/220V/230V/240V		
Unload Current	≤0.8A	≤0.4A	≤0.2A
Output Frequency	(50Hz±2Hz) or (60Hz±2Hz)		
Output Waveform	Pure sine wave		
Display	LED or LCD display		
USB Output Voltage / Current	5V@3.4A,9V@2A,12V@1.5A (Support QC3.0 fast charge up to 18W)		
Max. Output Efficiency	90%	92%	95%
Low Voltage Protection	"Alarm ""Bi"" with 2s interval +red and green lights flashing alternately restart automatically when voltage recover"		
Over Voltage Protection	" Alarm ""BiBi"" with 1s interval +red and green lights flashing alternately restart automatically when voltage recover"		
Over Load Protection	"Alarm ""Bi"" continuously +red light flashing / restart automatically when load power recover; If it is closed after twice recover, it need restart manually."		
Over Temp Protection	" Alarm ""BiBiBi"" with 1s interval +red and green lights flashing alternately restart when temp recover"		
Short Circuit Protection	Yes		
DC Reverse Connection Protection	Fuse burnt		
Low Voltage Alarm Range	10.5v±0.5v	21v±0.5v	42v±0.5v
Low Voltage Protection Range	9.5v±0.5v	19v±0.5v	38v±0.5v
Low Voltage Recover Range	12v±0.5v	23v±0.5v	46v±0.5v
Over Voltage Protection Range	15.5v±0.5v	31v±0.5v	62v±0.5v
Over Voltage Recover Range	14v±0.5v	28v±0.5v	56v±0.5v
Working Temperature	-10°C~50°C		
Cooling Method	Fan cooling (Temperature control)		
Unit Size	335mm*180mm*76mm		
N.W/G.W	3.42kg/4kg		


2000W Pure sine wave power inverter



Technical parameters

Model	P-2000W-12V	P-2000W-24V	P-2000W-48
Rated Power	2000W		
Peak Power	4000W		
DC Input Voltage Range	DC12V(9.5V-15.5V)	DC24V(19V-31V)	DC48V(38V-62V)
AC Output Voltage (Single Choice)	100V/110V/120V/220V/230V/240V		
Unload Current	≤0.9A	≤0.55A	≤0.3A
Output Frequency	(50Hz±2Hz) or (60Hz±2Hz)		
Output Waveform	Pure sine wave		
Display	LED or LCD display		
USB Output Voltage / Current	5V@3.4A,9V@2A,12V@1.5A (Support QC3.0 fast charge up to 18W)		
Max. Output Efficiency	90%	92%	95%
Low Voltage Protection	"Alarm ""Bi"" with 2s interval +red and green lights flashing alternately restart automatically when voltage recover"		
Over Voltage Protection	" Alarm ""BiBi"" with 1s interval +red and green lights flashing alternately restart automatically when voltage recover"		
Over Load Protection	"Alarm ""Bi"" continuously +red light flashing / restart automatically when load power recover; If it is closed after twice recover, it need restart manually."		
Over Temp Protection	" Alarm ""BiBiBi"" with 1s interval +red and green lights flashing alternately restart when temp recover"		
Short Circuit Protection	Yes		
DC Reverse Connection Protection	Fuse burnt		
Low Voltage Alarm Range	10.5v±0.5v	21v±0.5v	42v±0.5v
Low Voltage Protection Range	9.5v±0.5v	19v±0.5v	38v±0.5v
Low Voltage Recover Range	12v±0.5v	23v±0.5v	46v±0.5v
Over Voltage Protection Range	15.5v±0.5v	31v±0.5v	62v±0.5v
Over Voltage Recover Range	14v±0.5v	28v±0.5v	56v±0.5v
Working Temperature	-10°C~50°C		
Cooling Method	Fan cooling (Temperature control)		
Unit Size	365mm*210mm*92mm		
N.W/G.W	4.7kg/5.48kg		

3000W Pure sine wave power inverter



Technical parameters

Model	P-3000W-12V	P-3000W-24V	P-3000W-48V
Rated Power	3000W		
Peak Power	6000W		
DC Input Voltage Range	DC12V(9.5V-15.5V)	DC24V(19V-31V)	DC48V(38V-62V)
AC Output Voltage (Single Choice)	100V/110V/120V/220V/230V/240V		
Unload Current	≤1A	≤0.7A	≤0.4A
Output Frequency	(50Hz±2Hz) or (60Hz±2Hz)		
Output Waveform	Pure sine wave		
Display	LED or LCD display		
USB Output Voltage / Current	5V@3.4A, 9V@2A, 12V@1.5A (Support QC3.0 fast charge up to 18W)		
Max. Output Efficiency	90%	92%	95%
Low Voltage Protection	"Alarm ""BiBi"" with 2s interval +red and green lights flashing alternately restart automatically when voltage recover"		
Over Voltage Protection	" Alarm ""BiBi"" with 1s interval +red and green lights flashing alternately restart automatically when voltage recover"		
Over Load Protection	"Alarm ""BiBi"" continuously +red light flashing / restart automatically when load power recover; If it is closed after twice recover, it need restart manually."		
Over Temp Protection	" Alarm ""BiBiBi"" with 1s interval +red and green lights flashing alternately restart when temp recover"		
Short Circuit Protection	Yes		
DC Reverse Connection Protection	Fuse burnt		
Low Voltage Alarm Range	10.5v±0.5v	21v±0.5v	42v±0.5v
Low Voltage Protection Range	9.5v±0.5v	19v±0.5v	38v±0.5v
Low Voltage Recover Range	12v±0.5v	23v±0.5v	46v±0.5v
Over Voltage Protection Range	15.5v±0.5v	31v±0.5v	62v±0.5v
Over Voltage Recover Range	14v±0.5v	28v±0.5v	56v±0.5v
Working Temperature	-10°C~50°C		
Cooling Method	Fan cooling (Temperature control)		
Unit Size	445mm*210mm*92mm		
N.W/G.W	6.3kg/7.3kg		

4000W Pure sine wave power inverter



Technical parameters

Model	P-4000W-12V	P-4000W-24V	P-4000W-48V
Rated Power	4000W		
Peak Power	8000W		
DC Input Voltage Range	DC12V(9.5V-15.5V)	DC24V(19V-31V)	DC48V(38V-62V)
AC Output Voltage (Single Choice)	100V/110V/120V/220V/230V/240V		
Unload Current	≤1A	≤0.7A	≤0.4A
Output Frequency	(50Hz±2Hz) or (60Hz±2Hz)		
Output Waveform	Pure sine wave		
Display	LED or LCD display		
USB Output Voltage / Current	5V@3.4A,9V@2A,12V@1.5A (Support QC3.0 fast charge up to 18W)		
Max. Output Efficiency	90%	92%	95%
Low Voltage Protection	"Alarm ""Bi"" with 2s interval +red and green lights flashing alternately restart automatically when voltage recover"		
Over Voltage Protection	" Alarm ""BiBi"" with 1s interval +red and green lights flashing alternately restart automatically when voltage recover"		
Over Load Protection	"Alarm ""Bi"" continuously +red light flashing / restart automatically when load power recover; If it is closed after twice recover, it need restart manually."		
Over Temp Protection	" Alarm ""BiBiBi"" with 1s interval +red and green lights flashing alternately restart when temp recover"		
Short Circuit Protection	Yes		
DC Reverse Connection Protection	Fuse burnt		
Low Voltage Alarm Range	10.5v±0.5v	21v±0.5v	42v±0.5v
Low Voltage Protection Range	9.5v±0.5v	19v±0.5v	38v±0.5v
Low Voltage Recover Range	12v±0.5v	23v±0.5v	46v±0.5v
Over Voltage Protection Range	15.5v±0.5v	31v±0.5v	62v±0.5v
Over Voltage Recover Range	14v±0.5v	28v±0.5v	56v±0.5v
Working Temperature	-10°C~50°C		
Cooling Method	Fan cooling (Temperature control)		
Unit Size			
N.W/G.W			

5000W Pure sine wave power inverter



Technical parameters



Model	P-5000W-12V	P-5000W-24V	P-5000W-48V
Rated Power	5000W		
Peak Power	10000W		
DC Input Voltage Range	DC12V(9.5V-15.5V)	DC24V(19V-31V)	DC48V(38V-62V)
AC Output Voltage (Single Choice)	100V/110V/120V/220V/230V/240V		
Unload Current	≤1.2A	≤0.8A	≤0.5A
Output Frequency	(50Hz±2Hz) or (60Hz±2Hz)		
Output Waveform	Pure sine wave		
Display	LED or LCD display		
USB Output Voltage / Current	5V@3.4A,9V@2A,12V@1.5A (Support QC3.0 fast charge up to 18W)		
Max. Output Efficiency	90%	92%	95%
Low Voltage Protection	"Alarm ""Bi"" with 2s interval +red and green lights flashing alternately restart automatically when voltage recover"		
Over Voltage Protection	" Alarm ""BiBi"" with 1s interval +red and green lights flashing alternately restart automatically when voltage recover"		
Over Load Protection	"Alarm ""Bi"" continuously +red light flashing / restart automatically when load power recover; If it is closed after twice recover, it need restart manually."		
Over Temp Protection	" Alarm ""BiBiBi"" with 1s interval +red and green lights flashing alternately restart when temp recover"		
Short Circuit Protection	Yes		
DC Reverse Connection Protection	Fuse burnt		
Low Voltage Alarm Range	10.5v±0.5v	21v±0.5v	42v±0.5v
Low Voltage Protection Range	9.5v±0.5v	19v±0.5v	38v±0.5v
Low Voltage Recover Range	12v±0.5v	23v±0.5v	46v±0.5v
Over Voltage Protection Range	15.5v±0.5v	31v±0.5v	62v±0.5v
Over Voltage Recover Range	14v±0.5v	28v±0.5v	56v±0.5v
Working Temperature	-10°C~50°C		
Cooling Method	Fan cooling (Temperature control)		
Unit Size			
N.W/G.W			

6000W Pure sine wave power inverter



Technical parameters

Model	P-6000W-12V	P-6000W-24V	P-6000W-48V
Rated Power	6000W		
Peak Power	12000W		
DC Input Voltage Range	DC12V(9.5V-15.5V)	DC24V(19V-31V)	DC48V(38V-62V)
AC Output Voltage (Single Choice)	100V/110V/120V/220V/230V/240V		
Unload Current	≤1.2A	≤0.8A	≤0.5A
Output Frequency	(50Hz±2Hz) or (60Hz±2Hz)		
Output Waveform	Pure sine wave		
Display	LED or LCD display		
USB Output Voltage / Current	5V@3.4A,9V@2A,12V@1.5A (Support QC3.0 fast charge up to 18W)		
Max. Output Efficiency	90%	92%	95%
Low Voltage Protection	"Alarm ""Bi"" with 2s interval +red and green lights flashing alternately restart automatically when voltage recover"		
Over Voltage Protection	" Alarm ""BiBi"" with 1s interval +red and green lights flashing alternately restart automatically when voltage recover"		
Over Load Protection	"Alarm ""Bi"" continuously +red light flashing / restart automatically when load power recover; If it is closed after twice recover, it need restart manually."		
Over Temp Protection	" Alarm ""BiBiBi"" with 1s interval +red and green lights flashing alternately restart when temp recover"		
Short Circuit Protection	Yes		
DC Reverse Connection Protection	Fuse burnt		
Low Voltage Alarm Range	10.5v±0.5v	21v±0.5v	42v±0.5v
Low Voltage Protection Range	9.5v±0.5v	19v±0.5v	38v±0.5v
Low Voltage Recover Range	12v±0.5v	23v±0.5v	46v±0.5v
Over Voltage Protection Range	15.5v±0.5v	31v±0.5v	62v±0.5v
Over Voltage Recover Range	14v±0.5v	28v±0.5v	56v±0.5v
Working Temperature	-10°C~50°C		
Cooling Method	Fan cooling (Temperature control)		
Unit Size			
N.W/G.W			